

Katalog polskich transformatorów sieciowych firmy ZATRA

Typ	Moc	U pierwotne	U wtórne	Prad
TS 1/1	1W	220V	25V	0,4A
TS 2/10	2W	220V	10,5V	0,17A
TS 2/14	2W	220V	8,2V	0,22A
TS 2/15	2W	220V	10,1V	0,18A
TS 2/16	2W	220V	6V	0,22A
TS 2/18	2W	220V	2x 5,5V	2x 0,14A
TS 2/20	2W	220V	10,6V	0,2A
TS 2/22	2W	220V	8,2V	0,2A
TS 2/24	2W	220V	25V	0,04A
TS 2/31	2W	220V	2x 20V	2x 0,0506A
TS 2/32	2W	220V	6V	0,1A
TS 2/33	2W	220V	8,6V	0,16A
TS 2/34	2W	220V	10,1V	0,18A
TS 2/36	2W	220V	8,8V	0,22A
TS 2/38	2W	220V	24,0V	0,06A
TS 2/39	2W	220V	10,6V	0,2A
TS 2/4	2W	220V	5,2V	0,28A
TS 2/44	2W	220V	14V	0,1A
TS 2/45	2W	220V	10V	0,14A
TS 2/46	2W	220V	15,5V	0,08A
TS 2/5	2W	220V	21V	0,06A
TS 2/50	2W	24V	21V	0,06A
TS 2/6	2W	380V	21V	0,06A
TS 2/7	2W	240V	21V	0,06A
TS 3/2	3W	220V	2x 4,9V 5,6V	2x0,35A 0,16A
TS 3/3	3W	110V/220V	2x 4,2V	2x 0,35A
TS 3/8	3W	220V	2x 3,7V	2x 0,3A
TS 4/10	4W	220V	9,6V	0,26A
TS 4/12	4W	220V	7,0V	0,3A
TS 4/13	4W	220V	7,5V	0,32A
TS 4/14	4W	220V	2x17,8V	2x0,10A
TS 4/15	4W	220V	7,4V	0,31A
TS 4/16	4W	220V	9,6V	0,27A
TS 4/17	4W	220V	7,0V	0,30A
TS 4/18	4W	220V	8,8V	0,36A
TS 4/19	4W	220V	7,6V	0,32A
TS 4/20	4W	220V	7,6V	0,32A
TS 4/21	4W	220V	7,6V	0,32A
TS 4/22	4W	220V	8,8V	0,36A
TS 4/23	4W	220V	11,0V	0,15A
TS 4/25	4W	220V	25,0V; 5,0V; 18,0V	0,06A; 0,085A; 0,04A
TS 4/26	4W	220V	7,3V; 45,0V	0,3A; 0,3A
TS 4/28	4W	220V	5,6V	0,50A
TS 4/3	4W	230V/250V	42,0V; 9,4V; 15,8V	0,019A; 0,5A; 0,06A
TS 4/30	4W	220V	2x 12,0V	2x 0,15A
TS 4/31	4W	220V	25,0V; 2x 2,5V	0,09A; 2x 0,085A
TS 4/32	4W	220V	25,0V; 2x 11,0V	0,05A; 2x 0,10A
TS 4/33	4W	220V	9,0V	0,30A
TS 4/34	4W	220V	13,3V	0,21A
TS 4/35	4W	220V	7,0V	0,30A
TS 4/37	4W	220V	9,5V	0,30A
TS 4/38	4W	220V	7,0V	0,30A
TS 4/4	4W	220V/240V	45,0V; 9,4V; 15,8V	0,02A; 0,05A; 0,06A
TS 4/40	4W	210/ 120V; 220/ 240V	8,5V	0,50A
TS 4/6	4W	220V	28,0V; 9,5V; 25,0V	0,033A; 0,05A; 0,09A
TS 4/7	4W	220V	7,0V	0,3A
TS 4/8	4W	220V	2x12,5V; 1,0V	2x2,05A; 0,05A

TS 5/10	5W	220V	10,0V	0,5A
TS 5/14	5W	220V	7,3V	0,7A
TS 5/3	5W	220V	10,0V	0,5A
TS 5/5	5W	110V; 220V	15,6V	0,3A
TS 5/6	5W	220V	10,0V	0,5A
TS 5/9	5W	220V	8,0V	0,4A
TS 6/1	6W	110V 220V	5,5V	0,1A
TS 6/10	6W	220V	2x 11,5V	2x 0,25A
TS 6/12	6W	220V	8,5V	0,7A
TS 6/13	6W	220V	30,0V; 68,0V	0,1A; 0,03A
TS 6/15	6W	220V	6,0V	0,8A
TS 6/16	6W	110V 220V	8,5V	0,7A
TS 6/17	6W	220V	2x 9,2V; 10,0V	2x 0,26A; 0,1A
TS 6/19	6W	220V	2x 10,0V	2x 0,142A
TS 6/2	6W	110V 220V	5,5V	1,0A
TS 6/21	6W	220V	2x 8,5V	2x 0,28A
TS 6/23	6W	220V	2x 15,0V	2x 0,2A
TS 6/24	6W	127V 220V	10,1V; 45,0V	0,59A; 0,015A
TS 6/25	6W	110V 220V	10,1V	0,6A
TS 6/27	6W	220V	2x 11,5V; 5,6V	2x 0,25A; 0,3A
TS 6/28	6W	110V 220V	25,0V	0,2A
TS 6/3	6W	110V 220V	8,5V	0,7A
TS 6/30	6W	220V	8,5V	0,7A
TS 6/34	6W	220V	9,9V	0,5A
TS 6/35	6W	220V	9,9V	0,5A
TS 6/38	6W	110V 220V	6,0V; 7,0V	0,6A; 0,7A
TS 6/39	6W	220V	4,9V; 6,3V	0,7A; 0,7A
TS 6/4	6W	220V	8,5V	0,7A
TS 6/40	6W	220V	15,5V	0,3A
TS 6/41	6W	127V 220V	18,0V; 45,0V	0,2A; 0,015A
TS 6/42	6W	220V	2x 15,5V	0,2A
TS 6/45	6W	220V	2x 16,5V	0,22A
TS 6/46	6W	220V	9,0V	0,5A
TS 6/47	6W	110V 220V	2x 15,0V	2x 0,25A
TS 6/49	6W	110V 220V	8,5V	0,5A
TS 6/5	6W	220V	5,5V	1,0A
TS 6/51	6W	220V	220,0V	0,01A
TS 6/6	6W	220V	10,0V	0,5A
TS 6/9	6W	220V	6,1V	1,0A
TS 8/1	8W	220V	11,5V	0,6A
TS 8/10	8W	220V	2x 10,5V	2x 0,35A
TS 8/12	8W	110V 220V	7,5V	0,9A
TS 8/13	8W	110V 220V	2x 10,4V	2x 0,36A
TS 8/15	8W	220V	22,8V 0,8V	0,25A 0,4A
TS 8/16	8W	220V	2x 10,5V	2x 0,35A
TS 8/17	8W	220V	10,8V	0,5A
TS 8/18	8W	220V	2x 22,0V	2x 0,18A
TS 8/2	8W	220V	2x 24,0V; 20,0V	2x 0,7A; 0,08A
TS 8/24	8W	220V	2x 18,2V	2x 0,22A
TS 8/26	8W	220V	7,0V; 21,0V	0,15A; 0,33A
TS 8/28	8W	220V	2x 8,1V	2x 0,35A
TS 8/3	8W	220V	2x 10,1V	2x 0,36A
TS 8/30	8W	220V	7,4V; 8,8V; 13,0V	0,35A; 0,2A; 0,2A
TS 8/31	8W	220V	41,0V; 13,5V	0,5A; 0,35A
TS 8/32	8W	220V	45,0V; 18,0V; 13,2V	0,2A; 0,16A; 0,15A
TS 8/36	8W	220V	9,0V	0,6A
TS 8/37	8W	220V	13,5V; 41,0V; 2,2V	0,35A; 0,05A; 0,1A
TS 8/39	8W	220V	2x 7,7V	2x 0,6A
TS 8/6	8W	110V 220V	6,8V	1,2A
TS 8/7	8W	220V	11,5V	0,6A
TS 8/8	8W	220V	6,8V	1,1A

TS 8/9	8W	220V	8,25V	0,7A
TS 10/1	10W	220V	2x 9,2V; 7,7V; 3,3V	2x 0,35A; 0,23A; 0,24A
TS 10/13	10W	220V	8,8V; 8,2V	0,70A; 0,082A
TS 10/15	10W	220V	11,8V; 22,5V	0,15A; 0,3A
TS 10/19	10W	220V	45,0V; 13,0V; 9,0V	0,015A; 0,35A; 0,40A
TS 10/2	10W	220V	20,0V	0,35A
TS 10/21	10W	220V	45,0V; 18,0V; 8,0V	0,015A; 0,2A; 0,65A
TS 10/22	10W	110V 220V	2x 21,5V	2x 0,2A
TS 10/23	10W	220V 380V	2x 21,5V	2x 0,2A
TS 10/24	10W	110V 220V	2x 21,5V	2x 0,2A
TS 10/25	10W	220V 380V	2x 21,5V	2x 0,2A
TS 10/3	10W	110V 220V	9,1V	1,0A
TS 10/30	10W	220V	14; 8,5	0,3A; 0,6A
TS 10/4	10W	220V	13,5V	0,65A
TS 10/5	10W	110V 220V	9,1V	1,0A
TS 10/7	10W	110V 220V; 127V	12,0V; 23,0V	0,15A; 0,30A
TS 10/8	10W	220V	20,0V	0,35A
TS 12/1	12W	110V 220V	9,5V	2,0A
TS 12/10	12W	240V	9,1V	1,2A
TS 12/12	12W	220V	9,1V	1,2A
TS 12/2	12W	110V 220V	9,1V	1,2A
TS 12/3	12W	110V 220V	11,5V	1,0A
TS 12/4	12W	110V 220V	9,1V	1,2A
TS 12/6	12W	220V	19,4V; 8,8V	0,1A; 1,1A
TS 12/9	12W	220V	9,1V	1,2A
TS 15/1	15W	110V 220V	6,0V	2,5A
TS 15/12	15W	220V	2x 17,5V	2x 0,5A
TS 15/13	15W	220V	2x 28,5V	2x 0,25A
TS 15/14	15W	110V 220V	2x 15,7V	2x 0,5A
TS 15/15	15W	110V 220V	6,3V; 17,8V; 18,5V	1,33A; 0,1A; 0,1A
TS 15/16	15W	110V 220V	2x 13,5V	2x 0,5A
TS 15/17	15W	220V	32,8V; 16,5V; 10,8V; 5,5V	0,15A; 0,15A; 0,14A; 0,57A
TS 15/18	15W	220V	5,9V; 11,7V	0,4A; 0,94A
TS 15/19	15W	110V 220V	13,6V; 34,7V	0,54A; 0,17A
TS 15/2	15W	220V	6,0V	2,5A
TS 15/28	15W	127V 220V	67,0V; 2,0V	0,1A; 0,08A
TS 15/29	15W	110V 220V	9,4V	1,9A
TS 15/3	15W	220V	6,0V	2,5A
TS 15/30	15W	220V	265,0V; 83,0V; 12,1V; 6,15V	0,001A; 0,03A; 0,6A; 0,64A
TS 15/31	15W	220V	11,7V; 5,9V	0,9A; 0,4A
TS 15/32	15W	220V	8,7V	1,8A
TS 15/33	15W	220V	28,0V; 9,3V	0,35A; 0,5A
TS 15/34	15W	110V 220V	2x 13,5V	2x 0,5A
TS 15/35	15W	220V	13,5V; 6,3V; 83,0V; 280,0V	0,45A; 0,45A; 0,045A; 0,0015A
TS 15/37	15W	110V	8,7V	1,8A
TS 15/38	15W	220V	2x 15,7V	2x 0,5A
TS 15/39	15W	220V	2x 16,0V	2x 0,4A
TS 15/4	15W	220V	2x 15,7V	2x 2,5A
TS 15/41	15W	220V	2x 11,0V	2x 0,55A
TS 15/43	15W	220V	2x 19,5V	2x 0,3A
TS 15/5	15W	220V	2x 15,7V	2x 2,5A
TS 15/6	15W	220V	2x 15,7V; 6,3V; 10,0V	2x 0,3A; 0,4A; 0,25A
TS 15/7	15W	240V	2x 15,7V	2x 0,25A
TS 15/8	15W	220V	6,0V	2,5A
TS 15/9	15W	220V	28,0V; 9,3V	0,35A; 0,5A
TS 18/10	18W	220V	10,5V	1,3A
TS 18/12	18W	220V	2x6V	2x1,3A
TS 18/14	18W	220V	22,5V	0,8A
TS 18/15	18W	220V	14,8V	0,7A

TS 18/4	18W	220V	10,5V	1,6A
TS 18/8	18W	220V	13,3V	1,3A
TS 20/1	20W	220V	2x9V	2x1A
TS 20/10	20W	220V	2x9V	2x1,0A
TS 20/20	20W	220V	8,7V	2,3A
TS 20/23	20W	220V	2x13V	2x0,7A
TS 20/24	20W	220V	9V; 12V	2;1,5A
TS 20/25	20W	220V	6V	3,3A
TS 20/9	20W	220V	25V	0,7A
TS 25/11	25W	220V	15V; 9V	1,1A; 1,3A
TS 25/17	25W	220V	2x11,7V; 5,2V; 35V	2x1A; 0,5A; 0,05A
TS 25/25	25W	220V	13V	3A
TS 25/9	25W	220V	10V; 12V; 14V; 17V	1,2A; 1,2A; 1,2A; 1,2A
TS 30/33	30W	220	5,3V	6A
TS 40/38	40W	220V	20,5V; 6,1V	1,5A; 1,1A
TS 40/39	40W	220V	210V; 25V; 8V; 6,3V	0,04A; 0,8A; 0,05A; 1,9A
TS 40/43	40W	220V	16,6V; 18,4V	2A; 0,9A
TS 40/49	40W	220V	2x19,5V	2x1A
TS 40/52	40W	220V	2x19,8V	2x0,9A
TS 40/54	40W	220V	20V; 5,9V	1,8A; 1,1A
TS 40/74	40W	220V	17V; 18,4V	2,1A; 0,9A
TS 40/84	40W	220V	12V	4,6A
TS 40/87	40W	220V	2x7,4V	2x2A
TS 40/95	40W	220V	2x6V	2x2,6A
TS 50/11	50W	220V	2x7,5V	2x2,6A
TS 50/13	50W	220V	2x7V	2x2,6A
TS 50/17	50W	220V	2x18,5V; 2x18V	2x1A; 2x0,12A
TS 50/21	50W	220V	2x7V	2x2,6A
TS 50/47	50W	220V	2x13,5V	2x1,5A
TS 80/6	80W	220V	12,8V	5,35A
TS 90/2	90W	220V	2x10,5V	2x4,5A
TS 120/1	120W	220V	2x21,5; 2x17,6; 2x6,4	2x0,25A; 2x2,5A; 2x1A



Serwis Tv Wrocław : www.serwis-tv.com